

DC SQUID based on the mesoscopic multiterminal Josephson junction

M.H.S. Amin^a A.N. Omelyanchouk^{b,*} A.M.Zagoskin^{a,c}

^a*D-Wave Systems Inc., 320-1985 W. Broadway, Vancouver, B.C., V6J 4Y3,
Canada*

^b*B.I.Verkin Institute for Low Temperature Physics and Engineering, Ukrainian
National Academy of Sciences, Lenin Ave. 47, Kharkov 310164, Ukraine*

^c*Physics and Astronomy Dept., The University of British Columbia, 6224
Agricultural Rd., Vancouver, B.C., V6T 1Z1, Canada*

Abstract

A theory is offered for a novel device, mesoscopic four-terminal SQUID. The studied system consists of a mesoscopic four-terminal junction, one pair of terminals of which is incorporated in a superconducting ring and the other one is connected with a transport circuit. The nonlocal weak coupling between the terminals leads to effects of phase dragging and magnetic flux transfer. The behaviour of a four-terminal SQUID, controlled by the external parameters, the applied magnetic flux and the transport current is investigated. The critical current and the current voltage characteristics as functions of magnetic flux are calculated. In the nonlocal mesoscopic case they depend not only on the magnitude of the applied flux but also on its sign, allowing measurement of the direction of the external magnetic field.

Key words: SQUID, multiterminal, Josephson junction, nonlocal coupling.

PACS: 85.25.Cp, 74.80.Fp

The four-terminal SQUID is a superconducting device based on a four-terminal Josephson junction [1]. The multiterminal Josephson junctions (MTJ) generalizes the usual (two-terminal) Josephson junctions [2] to the case of weak coupling between several massive superconducting banks (terminals). Compared with two-terminal junctions, such systems have additional degrees of freedom and the corresponding set of control parameters, preset transport currents and (or) applied magnetic fluxes. As a result, the current- or voltage-biased and the magnetic flux-driven regimes can be combined in one multiterminal microstructure. One of the realizations of a MTJ presents the set of superconducting terminals, which are connected with the short dirty microbridges having a common centre (Fig.1a). In such (conventional) MTJ the nonlinear coupling between individual bridges is due to the fact that the superconducting order parameter in the common centre is a function of the currents through all the microbridges. See review of macroscopic quantum interference effects in conventional multiterminal microstructures in Ref.[3]. Another type of multiterminal Josephson junction is based on the weak coupling of bulk superconductors through the two-dimensional clean normal layer (Fig.1b). In such a mesoscopic ballistic 4-terminal junction [4] the nonlocal coupling of supercurrents is established due to the phase dependent local Andreev levels inside the weak link. The nonlocal weak coupling in mesoscopic MTJ leads to the effects of phase dragging and magnetic flux transfer [5,6]. In the present paper we consider the behaviour of a mesoscopic 4-terminal SQUID (Fig.2) emphasizing the specific features of mesoscopic case.

* Corresponding author, omelyanchouk.ilt.kharkov.ua

The studied system (Fig.2) consists of a mesoscopic four-terminal junction, one pair of terminals of which is incorporated in a superconducting ring and the other one is connected with a transport circuit. The system can be controlled by an external magnetic flux Φ^e and by the transport current I . Current J is the self-induced circulating current in the ring circuit with self-inductance L . The state of the 4-terminal junction is determined by the dynamical variables, phases φ_i of the complex off-diagonal potential $\Delta_0 \exp(i\varphi_i)$ in the i -th terminal ($i=1\dots 4$). In the 4-terminal case we have three independent phase differences. Phases θ and ϕ are the phase differences between terminals 2-1 and 3-4, respectively. Phase $\chi = 1/2(\varphi_1 + \varphi_2) - 1/2(\varphi_3 + \varphi_4)$ is the phase difference between the ring and the transport current circuit. The phase ϕ is related to the observable quantity, total magnetic flux threading the ring Φ , $\phi = \frac{2e}{\hbar}\Phi$. For given external parameters I and Φ^e , Gibbs potential for the 4-terminal SQUID in terms of variables ϕ, θ and χ has the form [6]:

$$U(\phi, \theta, \chi; I, \Phi^e) = \kappa \frac{(\phi - \frac{2e}{\hbar}\Phi^e)^2}{2\tilde{L}} - I\theta - \cos(\theta) - \kappa \cos(\phi) - 2 \left(\alpha \cos \frac{\theta}{2} \cos \frac{\phi}{2} - \beta \sin \frac{\theta}{2} \sin \frac{\phi}{2} \right) \cos(\chi). \quad (1)$$

The last three terms in Eq.(1) are the Josephson coupling energy. The coefficients κ, α, β in Eq.(1) determine the coupling between the different terminals. They depend on the geometry of the weak link and on the transparency D of $S - N$ interfaces. In a symmetric case of square N -layer and ideal transparency ($D=1$) they equal to : $\kappa = 1, \alpha = \sqrt{2}+1, \beta = \sqrt{2}-1$. The current I is measured in units of $I_0 = \pi\gamma_{12}\Delta_0(T)^2/4eT_c$, where γ_{12} is the inverse Sharvin resistance between the terminals 1 and 2. $\tilde{L} = (2e/\hbar)LI_0\kappa$ is the dimensionless self-inductance.

The specific feature of a mesoscopic 4-terminal SQUID is the appearance in the potential U of the term, proportional to coefficient β . Note, that even for a completely symmetrical mesoscopic MTJ we have $\beta \neq 0$, contrary to the conventional MTJ (Fig.1a). In the latter case β identically equals zero for any symmetry of microbridge configuration.

The minimization of U with respect to phases θ, ϕ, χ gives the equations

$$I = \sin \theta + \left[\alpha \sin \frac{\theta}{2} \cos \frac{\phi}{2} + \beta \cos \frac{\theta}{2} \sin \frac{\phi}{2} \right] \cos \chi, \quad (2)$$

$$\frac{\frac{2e}{\hbar} \Phi^e - \phi}{\tilde{L}} = \sin \phi + \frac{1}{\kappa} \left[\alpha \sin \frac{\phi}{2} \cos \frac{\theta}{2} + \beta \cos \frac{\phi}{2} \sin \frac{\theta}{2} \right] \cos \chi, \quad (3)$$

$$\cos \chi = \text{sign} \left[\alpha \cos \frac{\phi}{2} \cos \frac{\theta}{2} - \beta \sin \frac{\phi}{2} \sin \frac{\theta}{2} \right], \quad (4)$$

The system of Eqs.(2-4) describes the behaviour of a mesoscopic 4-terminal SQUID in the stationary state. It determines the magnetic flux in the ring $\Phi = \frac{\hbar}{2e} \phi$ as function of applied magnetic flux Φ^e and transport current I . The nonlocal Josephson coupling ($\beta \neq 0$) leads to the new effects. As follows from Eqs.(2-4) the magnetic flux Φ in the ring produces the phase difference θ on current driven junction 1-2 at zero current I flowing from terminal 1 to terminal 2. Similarly the transport current I induces in the ring the magnetic flux Φ in the absence of external flux Φ^e . The influence of the phase difference between one pair of terminals on the phase difference between another pair of terminals is what we call phase dragging effect in the mesoscopic 4-terminal junction. As applied to mesoscopic 4-terminal SQUID this effect results in the dependence of the critical current I_c (maximal value of I at which the system of equations (2-4) has the solution) not only on the absolute value but also on the sign of the applied magnetic flux Φ^e . The steady states domain in the

(I, Φ^e) plane is shown in Fig.3 for the case of small self-inductance $\tilde{L} \ll 1$. The boundary of the domain, curve $I_c(\Phi^e)$ (solid lines in Fig.3), is 2π periodic, but due to the terms proportional to β in Eqs.(2-4), it is not invariant under the transformation $\Phi^e \rightarrow -\Phi^e$. The symmetry is restored if we simultaneously change Φ^e on $-\Phi^e$ and I on $-I$. Note, that in conventional case ($\beta = 0$) the boundary of the steady state domain $I_c(\Phi^e)$ is symmetric with respect to the axes (I, Φ^e) (dashed line in Fig.3). Outside the steady state domain, the stationary solutions for (θ, Φ) are absent and system goes to the nonstationary resistive regime. We have studied the dynamical behaviour of the 4-terminal SQUID in the frame of the heavily damped resistively shunted junction (RSJ) model [2]. The features of the dynamical behaviour of the mesoscopic 4-terminal SQUID are again affected by the terms proportional to β , i.e. by nonlocal coupling. The current-voltage characteristics in the transport channel, $V(I)$, (V is the time averaged voltage between terminals 2 and 1) are shown in Fig.4 for different values of Φ^e . The voltage $V(I)$ in applied magnetic flux Φ^e depends on the sign of the Φ^e as well as critical current I_c . Thus, the mesoscopic 4-terminal SQUID can be used for direction-sensitive detection of weak magnetic fluxes. In addition, the system described by the potential (1) permits the existence of the bistable states even for negligible dimensionless self-inductance $\tilde{L} \rightarrow 0$, which can be exploited in the superconducting phase qubit design (see Ref.[7]).

References

- [1] R. de Bruyn Ouboter, A.N.Omelyanchouk, E.D.Vol, Physica B 205 (1995) 153.
- [2] A.Barone, G.Paterno, Physics and Applications of the Josephson Effect, Wiley,

New York, 1982.

- [3] R. de Bruyn Ouboter, A.N.Omelyanchouk, Superlatt. & Microstruct., **23**(1999)1005.
- [4] Malek Zareyan and A.N.Omelyanchouk, Low Temp. Phys. **25** (1999) 175.
- [5] A.N.Omelyanchouk and Malek Zareyan, Physica B 291 (2000) 81.
- [6] M.H.S.Amin, A.N.Omelyanchouk and A.M.Zagoskin, Low Temp. Phys. **27**, N8, (2001) 616.
- [7] M.H.S.Amin, A.N.Omelyanchouk, A.Blais, A.Maassen van den Brink, G.Rose, T.Duty and A.M.Zagoskin, Multi-terminal superconducting phase qubit (these proceedings).


Figure Captions

Fig.1: The multiterminal Josephson junction. Bulk superconductors 1,..4 are connected with the crossed microbridges (a) or are weakly coupled through the rectangular of a two-dimensional electron gas (b).


Fig.2: The mesoscopic four-terminal SQUID.

Fig.3: The steady state domain for mesoscopic four-terminal SQUID in plane (I, Φ_e) of the control parameters (solid line). Φ_e is measured in units $\hbar/2e$. Dashed line corresponds to the conventional four-terminal SQUID.

Fig.4: The current-voltage characteristics of a mesoscopic 4-terminal SQUID for different values of applied flux Φ_e . $\Phi_0 = \frac{h}{2e}$ is the superconducting flux quantum, $\tilde{L} = 0$.



a



b

Fig. 1.




Fig. 2.




Fig. 3.




Fig. 4.